



## L101 Upgrade Software from Hyper Terminal


- 1、 Device connect with power supply after into “Bootloader” status.
- 2、 Device is connected with PC via USB cable to open Hype terminal.




- 3、 Set “Name” on “ Connection Description” interface as above picture showed after press “OK” or “Cancel” directly, come to software main interface, select menu “File—Properties” as below displayed.




4、Select connect using COM, after click “Configure....”




Flow control select None




5、Click “Call” button from Toolbar :




Some information will show as below screenpoint:




Input “1” or “2” to choose software upgrade method, device will prompt “waiting for the firmware file to be sent...” as below showed :




6、Click menu” Transfer—Send File...” to get “Send File” interface as below screenshot displayed:



Select upgrade software and “Xmodem” protocol, after click “Send” :



Now software showed file sending status :



7、The sending interface will close automatically after file send out ,at the same time device output upgrade successfully and start operating upgraded software. Then close COM and software , the software upgrade ending.

```

11 - HyperTerminal
File Edit View Call Transfer Help

=====
=                Ulbo Tech L101 IAP App (Version 1.013)                =
=++-----                By Yang Bing      Aug  1 2014                =
=====

===== Main Menu =====

Press "1" to download firmware with verify
Press "2" to download firmware without verify
Press other key to exit bootloader

=====

Waiting for the firmware file to be sent ...
$$$$$$$$$$

Programming completed successfully!

Program run...

Connected 0:01:28  Auto detect  2400 8-N-1  SCROLL  CAPS  NUM  Capture  Print echo
  
```